

Data Link Series

DLR1160-2-N Datasheet



Features:

- High PD sensitivity for red light
- High speed up to 16 Mbps
- Low power consumption and current dissipation
- +3V power source

Typical Applications:

- Audio equipment
- Digital optical data link
- MD
- Sound card



Table of Contents

General Information	3
Package Dimensions	3
Pin Function	3
Device Selection Guide	4
Absolute Maximum Ratings	4
Electro-Optical Characteristics	
Measuring Method	6
PCB Layout For Electrical Circuit	7
Precautions for Using Method	7
Product Packaging Information	8
Revision History	10
About Edison Opto	10



General Information

The light receiving unit is a standard-package product with connector and opto-electric component packaged with PD and I/V amplifier IC. The function of unit changes the light signal into electric signal.

The unit is operated at +3V and the input signal is TTL compatible. The DLR1160-2-N has a maximum operating speed of 16 Mbps.

Package Dimensions




Figure 1. DLR1160-2-N series dimensions

Notes:

- 1. All dimensions are in millimeters.
- 2. General Tolerance:±0.2mm
- 3. Shutter color: Gray
- 4. Matrial: HTN (High Temperature Nylon

Pin Function

- 1. Vout
- 2. GND
- 3. Vcc



Device Selection Guide

Table 1. Device selection guide for DLR1160-2-N series.

Chip		Operating Voltage	Dissipation Current(mA)	Fiber	Coupling Light (dBm)	Input
IC Material	PD λp(nm)	(Vcc)	Тур.	Min.	Тур.	Max.
Si	700	3.0	3.5	-24	-	-14.5

Absolute Maximum Ratings

Table 2. Absolute maximum ratings for DLR1160-2-N series.

Parameter	Symbol	Rating	Unit
Supply Voltage	Vcc	6	V
Storage Temperature	Tstg	-30 to 80	°C
Operating Temperature	Topr	-20 to 70	°C
Soldering Temperature	Tsol	260*	°C

Note: *Soldering time ≤5s / 2 times.

Electro-Optical Characteristics

Table 3. DLR1160-2-N series electrico-optical characteristics.

Parameter	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Operating Voltage	V_{cc}	-	2.7	3.0	3.6	V
Peak Detective Wavelength	λ_{p}	-	-	700	-	nm
Transfer Speed		NRZ signal	0.1	-	16	Mbps
Receiving Distance		Using APF*	0.2	-	20	m
Pulse Width Distortion	Δ_{tw}	8 Mbps NRZ Signal	-20	-	20	ns
Input Light Power	P_{i}	*1	-24	-	-14.5	dBm
Dissipation Current	I _{cc}	*2	-	-	15	mA
High Level Output Voltage	V_{OH}		2.4	-	-	V
Low Level Output Voltage	V_{OL}		-	-	0.4	v
Rise Time	t _r	*3	-	-	25	ns
Fall Time	t _f	*3	-	-	25	ns
Low ->High propagation delay time	t _{PLH}	*3	-	-	100	ns
High->Low propagation delay time	t _{PHL}	*3	-	-	100	ns
Jitter time	Δ_{tj}	*3	-	1.5	15	ns

Note: *Light Input after APF should satisfy Pi range.

The DLR1160-2-N light receiving unit satisfies EIAJ CP-1201 digital audio interface standard.



Reliability Test Items

The following table describes operating life, mechanical, and environmental tests performed on DLR1160-2-N series package.

Table 4. Operating life, mechanical, and environmental characteristics for DLR1160-2-N

No.	ltem	Test Condition	Test Hour/Cycle	Samples	Number (n) Failure (c)
1	Soldering Heat	260°C±5°C	5 sec./2times	22	n=22, c=0
2	High temp. & Hum. storage	Ta=80°C, 90%RH	500	22	n=22, c=0
3	High temp. storage	Ta=80°C	500	22	n=22, c=0
4	Low Temp. storage	Ta=-30°C	500	22	n=22, c=0
5	Temp. cycling	-30°C ~~ 80°C (30min) (30min)	20	22	n=22, c=0
6	High Temp. Operation life	Ta=60°C, Vcc=5V ON	500	22	n=22, c=0
7	Repeated operation	500 times	Coupling force < 2 kg 0.4 kg <detaching <2kg<="" force="" td=""><td>22</td><td>n=22, c=0</td></detaching>	22	n=22, c=0

 I_{cc} (dissipation current): CURRENT ATTENUATE DIFFERENCE < 20% $T_{\mbox{\tiny PLH}}$ (propagation L $\,$ H delay time): DELAY TIME DIFFERENCE < 20%

 $T_{\mbox{\tiny PHL}}$ (propagation H $\,$ L delay time): DELAY TIME DIFFERENCE < 20%

 T_r (rise time): TIME DIFFERENCE < 20% T_f (fall time): TIME DIFFERENCE < 20%



Measuring Method

*1. Maximum receiver input optical power / Minimum receiver input optical power




Figure 2. DLR1160-2-N maximum receiver input optical power / minimum receiver input optical power

*2. Current dissipation measuring method




Figure 3. DLR1160-2-N Current dissipation measuring method

*3. Pulse response and jitter measuring method




Figure 4. DLR1160-2-N pulse response and jitter measuring method



PCB Layout For Electrical Circuit




Figure 5. DLR1160-2-N PCB layout for electrical circuit

Notes:

- 1. Unit: mm
- 2. Unspecified tolerance: ±0.2mm
- 3. Substrate Thickness: 1.6 mm

Precautions for Using Method

- 1.Connect a by-pass capacitor (0.1uF) close to the DLR1160-2-N within 7 mm of the unit lead frame.
- 2.Take proper electrostatic-discharge (ESD) precautions while handling these devices. These devices are sensitive to ESD.




Figure 6. DLR1160-2-N precautions for using method



Product Packaging Information

Table 5. Product packaging information for DLR1160-2-N series.

ltem	Quantity	Total	Dimensions(mm)
Tray	100	100 pcs	13.5*27*2 cm
Вох	10 tray/box	1000 pcs	29*29*10.5 cm
Carton	4 box/carton	4000 pcs	60*31*25.8 cm




Figure 7. DLR1160-2-N product packaging information



Material Description




Figure 8. DLR1160-2-N material description

Table 6. Materail Description for DLR1160-2-N series.

ITEM	NAME	MATERIAL	FINISH	NOTE
1	IC	Si	-	-
2	Silver Epoxy	Ag+Epoxy	-	-
3	Gold Wire	Au	-	-
4	Mold Compound	Ероху	-	-
5	Lead Frame	Phosphor Bronze	Tin	-
6	Fix Pin	Cu	Tin	-
7	Housing	HTN	-	UL94V-0
8	Shutter	HTN	-	UL94V-0
9	Springy	Stainless	-	-



Revision History

Table 7. Revision history of DLR1160-2-N series datasheet

Versions	Description	Release Date
1	1. Establish a Datasheet.	2006/05/02
2	1. Modify packaging information.	2012/07/12

About Edison Opto

Edison Opto is a leading manufacturer of high power LED and a solution provider experienced in LDMS. LDMS is an integrated program derived from the four essential technologies in LED lighting applications- Thermal Management, Electrical Scheme, Mechanical Refinement, Optical Optimization, to provide customer with various LED components and modules. More Information about the company and our products can be found at www.edison-opto.com

Copyright©2012 Edison Opto. All rights reserved. No part of publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photo copy, recording or any other information storage and retrieval system, without prior permission in writing from the publisher. The information in this publication are subject to change without notice.

www.edison-opto.com

For general assistance please contact: service@edison-opto.com.tw

For technical assistance please contact: LED.Detective@edison-opto.com.tw